

Model 4001



40 Channel CB Radio With 4-Watt Output Power and Switchable ANL

40th
Anniversary
Radio

**Celebrating 40
Years of quality
CB radios.**



**3 Year
Warranty**



40 Channel CB Radio With 4-Watt Output Power and Switchable ANL

FEATURES

- **40-Channel Phase Lock Loop Tuner**
Precision electronic locking onto your selected channel
- **4-Watt Output Power**
Provides maximum communication range
- **Dual Conversion Superheterodyne Receiver**
Advanced technology to ensure crystal clear reception
- **Squelch Control**
Eliminates unwanted background noise
- **RF Gain**
Adjusts reception sensitivity (range) for clear communication
- **Filter Switch**
For enhanced noise filtering
- **CB/PA Switch**
Toggles easily between public address and normal CB operation
- **ANL**
Automatic Noise Limiter cuts ignition noise
- **Large LED Channel Indicator**
Displays the active CB channel
- **Illuminated Power Meter**
Measures signal output strength; easy to read, even at night
- **Locking Microphone Connector**
Easy to connect microphone locks securely to your CB



Model 4001

Other Midland Products

GMRS 2-Way Radios



Weather Radios



CB Radios



Marine Radios



SPECIFICATIONS

Size:	6 1/2" W x 2 3/8" H x 7 1/4" D
Unit Weight:	4 lbs., 3.5 oz.
Transmit Power:	4 Watts
Frequency Control:	Phase Lock Loop (PLL)
Receiver Sensitivity:	Less than 0.8 uV for 10dB SN+N/N
Receiver Selectivity:	60dB
Controls:	On/Off/Volume, Channel selector, Squelch Control, Mic Control, RF gain Control, Bright/Dim Switch, ANL Switch, Filter On/Off and CB/PA Switch
Jacks & Connectors:	Microphone, 50-ohm antenna, 8-ohm external speaker, PA speaker and DC power cord
Accessories:	500-ohm Push-To-Talk Microphone with Clip, Coil Cord and Screw-Type Connector, Slotted Mounting Adjustable Bracket, Hardware, DC Power Cord with 3-Pin Connector and Owner's manual.

